




HPF-560 HIGH PASS FILTER SPECIFICATIONS (PREVIEW)

Customer: TKI Smp.NO: CS-20160113-1			<u>PICTURE</u>																																									
◆ MECHANICAL SPECIFICATIONS <table border="1"> <thead> <tr> <th><u>ITEM</u></th> <th><u>DESCRIPTION</u></th> <th><u>UNIT</u></th> </tr> </thead> <tbody> <tr> <td>Housing</td> <td>Copper Tube</td> <td></td> </tr> <tr> <td>Connector</td> <td>75Ω, Male & Female "F" type</td> <td></td> </tr> <tr> <td>Connector Screw Thread</td> <td>W 3/8"-32UNEF</td> <td>inch</td> </tr> <tr> <td>Dimensions</td> <td>21(φ)×57(L)</td> <td>mm</td> </tr> <tr> <td>Net Weight</td> <td>48</td> <td>g</td> </tr> </tbody> </table>			<u>ITEM</u>	<u>DESCRIPTION</u>	<u>UNIT</u>	Housing	Copper Tube		Connector	75Ω, Male & Female "F" type		Connector Screw Thread	W 3/8"-32UNEF	inch	Dimensions	21(φ)×57(L)	mm	Net Weight	48	g																								
			<u>ITEM</u>	<u>DESCRIPTION</u>	<u>UNIT</u>																																							
			Housing	Copper Tube																																								
			Connector	75Ω, Male & Female "F" type																																								
			Connector Screw Thread	W 3/8"-32UNEF	inch																																							
			Dimensions	21(φ)×57(L)	mm																																							
			Net Weight	48	g																																							
<u>Label</u>																																												
<table border="1"> <tr> <td> High Pass Filter HPF-560 MADE IN TAIWAN </td> </tr> </table>		High Pass Filter HPF-560 MADE IN TAIWAN																																										
High Pass Filter HPF-560 MADE IN TAIWAN																																												
◆ ELECTRICAL SPECIFICATIONS <table border="1"> <thead> <tr> <th><u>ITEM</u></th> <th><u>MIN</u></th> <th><u>TYP</u></th> <th><u>MAX</u></th> <th><u>UNIT</u></th> </tr> </thead> <tbody> <tr> <td>Frequency Range</td> <td></td> <td>5~1000</td> <td></td> <td>MHz</td> </tr> <tr> <td>Impedance</td> <td></td> <td>75</td> <td></td> <td>Ω</td> </tr> <tr> <td>Pass Band</td> <td></td> <td>560~1000</td> <td></td> <td>MHz</td> </tr> <tr> <td>Insertion Loss (560~1000 MHz)</td> <td></td> <td>2.0</td> <td>2.5</td> <td>dB</td> </tr> <tr> <td>Return Loss (560~1000 MHz)</td> <td>13</td> <td>20</td> <td></td> <td>dB</td> </tr> <tr> <td>Stop Band</td> <td></td> <td>5~504</td> <td></td> <td>MHz</td> </tr> <tr> <td>Rejection (5~504MHz)</td> <td>48</td> <td>50</td> <td></td> <td>dB</td> </tr> </tbody> </table>			<u>ITEM</u>	<u>MIN</u>	<u>TYP</u>	<u>MAX</u>	<u>UNIT</u>	Frequency Range		5~1000		MHz	Impedance		75		Ω	Pass Band		560~1000		MHz	Insertion Loss (560~1000 MHz)		2.0	2.5	dB	Return Loss (560~1000 MHz)	13	20		dB	Stop Band		5~504		MHz	Rejection (5~504MHz)	48	50		dB		
<u>ITEM</u>	<u>MIN</u>	<u>TYP</u>	<u>MAX</u>	<u>UNIT</u>																																								
Frequency Range		5~1000		MHz																																								
Impedance		75		Ω																																								
Pass Band		560~1000		MHz																																								
Insertion Loss (560~1000 MHz)		2.0	2.5	dB																																								
Return Loss (560~1000 MHz)	13	20		dB																																								
Stop Band		5~504		MHz																																								
Rejection (5~504MHz)	48	50		dB																																								

MODEL NO.	DATE	PREVIEW	PAGE/TOTAL
HPF-560 High Pass Filter	20160113	V1.1	1/2



HPF-560

Insertion Loss, Rejection and Return Loss

Span: 1000MHz

2016/1/13 上午 09:24:07



Fig.1

MODEL NO.	DATE	PREVIEW	PAGE/TOTAL
HPF-560 High Pass Filter	20160113	V1.1	2/2